




Q-CAP WURM™ FOR TUNABLE APPLICATIONS

24VDC Flexible Fixtures





Q-CAP WURM™ FOR TUNABLE APPLICATIONS

24VDC Flexible Fixtures

B. FIELD CUTTABLE Q-CAP

B1 PRODUCT	B2 MOUNTING	B3 RATED	B4 CCT	B5 WATTAGE	B6 LENS	B7 WIRE INPUT/OUTPUT	B8 CONNECTOR/WIRE IN	B9 CONNECTOR/WIRE OUT	B10 END CAPS	B11 LENGTH (IN)	B12 EXACT/ OPTIMAL
WURM-FC-DW		DRY			ENC/CL	S1		N/A	WH	48"	N/A

Sample Part Number: **WURM-DW-WSCS-DRY-24/30-1.5HE-ENC/CL-P1-BW-BW-N/A-48"-E**

B1 PRODUCT WURM-FC-DW LED engine is built with 3 wires requiring 0-10v, DMX or DALI control. Using DALI, DMX, or non QTL power supplies may double watts/ft. See last page for compatible power supplies.	B2 MOUNTING MCS WSCS BN-UD-SST-16' BN-UD-SST-32' BN-UD-WH-16' BN-UD-WH-32' White snug clip only for indirect cove use, not intended for hanging fixtures upside down.	B3 RATED DRY IP20	B4 CCT 24/30 2400K/3000K 27/40 2700K/4000K	B5 WATTAGE 1.5HE 1.5WHE-SO 2.5HE 2.5WHE-HO SO: Standard Output HO: High Output
B6 LENS ENC/CL Encapsulated in Clear For representation of LED visibility, see Diode Visibility section on following pages	B7 WIRE INPUT/OUTPUT S1 Single 1 (Input only) - End Feed	B8 CONNECTOR/WIRE IN BW Bare Wire (Standard 24") CON6 Connector 6" CON24 Connector 24" BW: Standard length is 24", Max length is 120". Request custom length by writing in part number next to BW (example: BW48)	B9 CONNECTOR/WIRE OUT N/A Closed End (No feed)	
B10 END CAPS WH White Due to cutting, white endcaps are not available.	B11 LENGTH (IN) 48" Nominal Starting Run length is 48.38" for S1 Each cut point subtracts from the Starting Run Length 1.5HE & 2.5HE have a 2" cut point S1 can be cut down to as little as 2.38"	B12 EXACT/OPTIMAL N/A		


Single



Q-CAP WURM™ FOR TUNABLE APPLICATIONS


24VDC Flexible Fixtures

1 PRODUCT - DIMENSIONS




Profile
(Standard)


BEND RADIUS



FLEXIBILITY




2 MOUNTING



White Snug Clip Small
Indirect uplight


To order separately use WSCS

Each clip comes with a #6x5/8" flat
screw



Magnetic Clip Small
Cove use only

To order separately use MCS
each clip comes with a #6x1 1/4" screw



BENDIT Channel
Vertical Stainless Steel
Flexible Channel

Continuous mounting solution for
flexible fixtures, 16' or 32' field
cuttable lengths

To order separately use either
STND-QCAP-BN-UD-S-SST-16',
STND-QCAP-BN-UD-S-SST-32',
STND-QCAP-BN-UD-S-WH-16', or
STND-QCAP-BN-UD-S-WH-32'

64 #4-40 1/2" screws provided per
16'



Q-CAP WURM™ FOR TUNABLE APPLICATIONS

24VDC Flexible Fixtures

4 / 5 DELIVERED LUMENS

[Calculated L70 = 40000 hrs]
Tested with WURM-DW-WSCS-DRY

CCT	15HE W/FT		2.5 HE W/FT	
	ENC/CL	ENC/CL	ENC/CL	ENC/CL
	LM	CRI	LM	CRI
2400K	133	92	198	92
2700K	126	96	201	97
3000K	132	97	206	97
4000K	142	97	225	98

6 DIODE VISIBILITY



ENC/CL - Clear encapsulation

ENC/TL - Translucent encapsulation

TEMPERATURE RATINGS


	DW 1.5 HE W/FT		DW 3.0 HE W/FT		DW 2.5 HE W/FT		DW 5.0 HE W/FT	
	QTL power supply other than DALI, DMX		DALI, DMX, or non-QTL power supply		QTL power supply other than DALI, DMX		DALI, DMX, or non-QTL power supply	
	Min	Max	Min	Max	Min	Max	Min	Max
Ambient Operating Temp - Surface	-4°F	140°F	-4°F	120°F	-4°F	120°F	-4°F	100°F
Storage Temp	-4°F	140°F	**	**	-4°F	140°F	**	**
Installation Temp	50°F	100°F	**	**	50°F	100°F	**	**

BUG RATING

WATTAGE	B	U	G
6.0 (ALL CCTs), 3.0HE (ALL CCTs), 5.0HE (ALL CCTs)	B0	U1	G0


7 WIRE INPUT/OUTPUT

SINGLE (Input only)



End Feed

PASS THROUGH (Input/Output) - Only applicable for Non-Field Cuttable Q-CAP




End Feed



Q-CAP WURM™ FOR TUNABLE APPLICATIONS


24VDC Flexible Fixtures

CONFIGURATION OPTIONS



Field Cuttable - Continuous End to End Feed

FIELD CUTTABLE MARKING




Field cuttable fixtures are sold in 4' increments and go at the end of a run, allowing for easy field adjustment



Note: Only FC fixtures are field cuttable — Do not attempt to cut non FC fixtures.
Cut only on the marked cut lines. Only cut from non-feed end. Do not attempt to cut while power is on.


8 / 9 CONNECTOR/WIRE - IN/OUT

Connector/Wire In or Out not needed to specify product. Typical selection is S1 for Wire Input/Output, BW for Connector/Wire In, N/A for Connector/Wire Out, and WH for End Caps



10 END CAPS (NO FEED)


WH
(only used in
A. Non-Field Cuttable
Q-CAP)



White endcaps
.11" added at end
.24" dim spot

END CAPS (WITH FEED)

End Feed
S1, P1



White endcaps
.0" added at end
.38" dim spot


11 LENGTH - WIRING DETAIL



Q-CAP WURM™ FOR TUNABLE APPLICATIONS

24VDC Flexible Fixtures

Available in 2" increments 12"-191"




12 EXACT/OPTIMAL FIXTURE LENGTH

[E/O Length Calculator →](#)

[E/O Explained →](#)

Exact fixtures are the exact length specified. Optimal fixtures' length is rounded down based on LED cut points to allow the fixture to be illuminated end to end. For runs with multiple fixtures that need to fill a specific length, it's recommended to order all optimal fixtures with an exact fixture at the end of the run.



DW LENGTHS BY INCH

Available in any length in between 12" and 191", chart below shows example lengths. Exact fixtures are the length specified. Optimal fixtures' length is rounded down with illumination end to end. All fixtures' tolerance is +0 - 1/8". Consult factory for lengths under 12".

EXACT LENGTH

Requested Length	Potential dim spot on either end of fixture
12"	1"
13"	.5"
14"	1"
15"	.5"
16"	1"
17"	.5"
18"	1"
19"	.5"
20"	1"
21"	.5"
22"	1"
23"	.5"
24"	1"
36"	1"
48"	1"
60"	1"
72"	1"
84"	1"
96"	1"

OPTIMAL LENGTH: highlighted rows are closest to requested nominal length

Requested Nominal Length	S1	P1
	S1	P1
12"	10.63"	10.75"
13"	12.63"	12.75"
14"	12.63"	12.75"
15"	14.63"	14.75"
16"	14.63"	14.75"
17"	16.63"	16.75"
18"	16.63"	16.75"
19"	18.63"	18.75"
20"	18.63"	18.75"
21"	20.63"	20.75"
22"	20.63"	20.75"
23"	22.63"	22.75"
24"	22.63"	22.75"
36"	34.63"	34.75"
48"	46.63"	46.75"
60"	58.63"	58.75"
72"	70.63"	70.75"
84"	82.63"	82.75"
96"	94.63"	94.75"



Q-CAP WURM™ FOR TUNABLE APPLICATIONS

24VDC Flexible Fixtures


COMPATIBLE POWER SUPPLIES

See power supplies cut sheets for more information. Data subject to change, all data has +/- 5% tolerance.

DIM TO LEVEL	INDOOR	OUTDOOR
	DW-HE Tunable Applications	DW-HE Tunable Applications
0.1%	QT-CAB-eLED+DALI-DT6 QT-CAB-eLED+DALI-DT8 QT-CAB-eLED+DALI-DT8-AWN QT-CAB-eLED+TW QT-CAB-eLED+TW-AWN QTM-eLED+DALI-DT6 QTM-eLED+DALI-DT8 QTM-eLED+DALI-DT8-AWN QTM-eLED+TW QTM-eLED+TW-AWN QZ-DMX	Q-SET-QZ-DMX QOM-eLED+DALI-DT6 QOM-eLED+DALI-DT8 QOM-eLED+PS-DALI-DT6 QOM-eLED+PS-DALI-DT8 QOM-eLED+TW QZ-DMX
1%	QZ-DALI-DT8	Q-SET+QZ-DALI-DT8 QZ-DALI-DT8
10%	Non-Dim Power Supply with TW App Dongle	

DIMMING PROTOCOL	INDOOR	OUTDOOR
	DW-HE Tunable Applications	DW-HE Tunable Applications
0-10V	QT-CAB-eLED+TW QT-CAB-eLED+TW-AWN QTM-eLED+TW QTM-eLED+TW-AWN	QOM-eLED+TW
Lutron Athena	QT-CAB-eLED+DALI-DT8-AWN QT-CAB-eLED+TW-AWN QTM-eLED+DALI-DT8-AWN QTM-eLED+TW-AWN	
DMX LED wattage must be doubled for DW-HE products	QZ-DMX	Q-SET-QZ-DMX QZ-DMX
DALI-2: DT6 LED wattage must be doubled for DW-HE products except for AWN	QT-CAB-eLED+DALI-DT6 QTM-eLED+DALI-DT6	QOM-eLED+DALI-DT6
DALI-2: DT8 LED wattage must be doubled for DW-HE products except for AWN	QT-CAB-eLED+DALI-DT8 QT-CAB-eLED+DALI-DT8-AWN QTM-eLED+DALI-DT8 QTM-eLED+DALI-DT8-AWN QZ-DALI-DT8	Q-SET+QZ-DALI-DT8 QOM-eLED+DALI-DT8 QZ-DALI-DT8
SCENE App Dimmed	Non-Dim Power Supply with TW App Dongle	

COMPATIBLE MOUNTING ACCESSORIES






Q-CAP WURM™ FOR TUNABLE APPLICATIONS

24VDC Flexible Fixtures

COMPATIBLE WIRING ACCESSORIES

Q-mini-J5



UL Listed, miniature junction box, DRY/DMP (WET rated with silicone)

COMPATIBLE CONTROL ACCESSORIES

SCENE APP DONGLE



Wi-Fi or Bluetooth Connectivity

COMPATIBLE APPS

NFC APP



Read and write DMX addresses and adjust voltage